

Kulttuuritalo Virta, Karelia-sali, DMX patch 2025

	DMX addr.	Amount	Fixture	Mode	Ch	Location
UNI 1	DMX UNIVERSE 1: front light truss / dimmers / hazer					
	1, 30	2	Robe ColorSpot 1200E AT Profile	mode 1	29ch	front light truss
	59, 104, 149, 194	4	Robe ROBIN MMX Blade	mode 1	45ch	front light truss
	239–244	6	2kW profile (dimmer)			bridge (above FOH)
	245–248	4	0,75 kW profile (dimmer)			tower, stage right
	253–256	4	0,75 kW profile (dimmer)			tower, stage left
	257–262	6	<i>(free dimmer ch)</i>			stage floor *
	263	1	Pea Soup hazer		1ch	wall, stage right
	264	1	Hazer fan		1ch	wall, stage right
	UNI 2	DMX UNIVERSE 2: stage truss – Spiider / Atomic / dimmers				
1, 50, 99, 148, 197, 246, 295, 344		8	Robe Spiider	mode 1	49ch	stage truss
393		1	Martin Atomic 3000		4ch	stage truss
	397–408	12	PAR64 1kW (dimmer)			stage truss *
UNI 3	DMX UNIVERSE 3: Arolla					
	1, 38, 75, 112, 149, 186, 223, 260	8	Clay Paky Arolla Profile MP		37ch	stage truss
UNI 4	DMX UNIVERSE 4: audience light / stage work light					
	1–4	4	Stage work light (dimmer)			ceiling
	5–12	8	Audience light (dimmer)			ceiling

* Dimmer channel outputs can be placed in different locations on the stage. Please let us know well in advance if this is needed.

Himmenninkanavia voidaan sijoittaa eri puolille lavaa. Mikäli tämä on tarpeen, ilmoittakaa asiasta hyvissä ajoin tekniselle henkilökunnalle.